

## Installation PCMCIA V.90 under Windows 2000

- a. Plug in the card into the PCMCIA-Slot (TYP II or TYP III). If you have problems to find the right slot, have a look at the manual of your PC or ask the manufacturer respectively your PC-dealer. Make sure that the card is plugged in tough.
- b. Connect the card with the delivered phone cable (possibly with adapter) with the N-Slot at the wall socket of the phone-line.
- c. Start your PC.
- d. The modem will be installed, without a message, as a standard PCMCIA CARD Modem. You can verify this under "start – settings – control panel – telephone and modemooption".
- e. Now go to "*start – settings – control panel – system*" and click the register card *Hardware* and there *device manager*. Under *modem*, you will find the PCMCIA Card. Make a double click to open the file and have a look at the *properties*.
- f. Change the register card to *driver* and push the button "*update driver*". The assistant for the device updates will be started. Confirm with "*Next*".
- g. "*This assistant will update the driver for the following device: Standard PCMCIA Card. What do you want to do?*" Choose the option "*Search the best driver for the device*" and push the button "*Next*".
- h. Insert the disc with the label "*Driver disc*" into your CD-ROM, activate the window "*Search other sources*" and go further with "*Next*".
- i. The following message appears: "*Found another driver for this device: a:\fmcv11n.inf*". Push the button "*Next*".
- j. The driver has no digital signature – continue the installation with "*Yes*".
- k. "*The software for this device has been installed: PCMCIA V.90 Fax Modem Card.*" Confirm with "*Finish*".
- l. Leave the device manager and the control panel.

### Installation of the modem utilities (necessary to change the country settings):

Put in the disc with the label "*World Traveler Modem Setup Utility*" and start the setup.exe. Now the utilities will be installed and you can use them under *start – program – World Travel*.